



- 6W 100V Loudspeaker
- Size 5" (130mm)
- Quick Mount
- Shock-resistant Housing
- High Efficiency
- Excellent Sound Quality

The SPCF-06W-50 is a 6W 100V flush mount ceiling loudspeaker, which has a 5" (130mm) full-range chassis providing excellent sound quality with speech and background music. The loudspeaker is fitted with a 100V transformer which has three power adjustment tapings of 6W, 3W, and 1.5W.

The SPCF-06W-50 has a powder coated metal chassis and grille, with the powder coated finish giving good long-term protection and resistance to corrosion. As standard, the loudspeaker is coloured to match RAL9010 'Pure White'. Alternatively, the loudspeakers can be supplied in any four-digit RAL or NCS colour, as a special order.

Spring clamps provide quick and easy ceiling mounting, with a possible ceiling thickness of between 2mm and 45mm. An inner ring attachment prevents the grille from falling. The 100V loudspeaker line cabling is connected to a two-pin ceramic block (maximum cable cross section is 8mm²). For additional reliability a thermal fuse is fitted, and the loudspeaker chassis is damp-resistant.

Please note that, although very thin ceilings can be used as a mounting surface, it should be ensured that the ceiling thickness and strength are appropriate to the weight (0.86 kg) of the loudspeaker, and to the thickness and weight of the 100V line loudspeaker cable.

This loudspeaker is optionally available with a DC blocking capacitor fitted in order to provide compatibility with DC loudspeaker line monitoring systems. The part number for this DC monitoring compatible version is SPCF-06W-50-DC.

Enhanced Acoustic Simulator for Engineers (EASE) data for this speaker is available on request.



Measurements according to DIN IEC 268-5
RoHS compliant (2011/65/EU)

Loudspeaker for public address systems.

Rated voice voltage: 100V
Rated voice/noise power: 6W



This product must be disposed of in accordance
with the WEEE directive.

Failure to use the equipment in the manner described in the product
literature will invalidate the warranty.

WEE/JB1444YU

Made for:

Application Solutions (Safety and Security) Limited

Unit 17 - Cliffe Industrial Estate

Lewes - East Sussex - BN8 6JL - UK

Tel: +44(0)1273 405411 Fax: +44(0)1273 405415

www.asl-control.co.uk

Copyright © 2018 Application Solutions (Safety and Security) Limited
All rights reserved.

Information contained in this document is believed to be accurate. However, no
representation or warranty is given and Application Solutions (Safety and
Security) Limited assumes no liability with respect to the accuracy of such
information.

Installation

1. Check that the ceiling thickness is between 2mm and 45mm, with a thickness and strength which is appropriate to the weight (0.86 kg) of the loudspeaker.
2. The 100V audio power cable should have a maximum cable cross section of 8mm², or a maximum cable cross section of 2 x 2mm² when daisy-chain wiring is used.
3. Make a ceiling cut-out of 167 mm diameter.
4. Separate the loudspeaker ring and loudspeaker grille and chassis assemblies.
5. Place the outer loudspeaker ring up into the ceiling cut out.
6. Reach through the loudspeaker ring, and release the spring clips to fix the loudspeaker ring in place. The spring clips should be released one at a time by pulling them back and to one side, away from their restraining hooks. The springs will clamp the loudspeaker ring into place in the ceiling.
7. Pull the audio power cable or cables down through the loudspeaker ring opening.
8. Bring the loudspeaker grille assembly up to the ceiling, and connect the audio power cabling to the ceramic terminal block.
9. Mount the grille assembly into the loudspeaker ring. This is done by aligning the grille's three mounting slots with the three pop rivets in the loudspeaker ring. Push the grille into place, while turning it clockwise to engage the grille support notches. A hooked fixing tool is provided in order to facilitate turning the grille, however ensure that the hook is not placed more than 5mm from the outer ring, or else the loudspeaker cone may be damaged.

Service and Warranty

This product carries a full warranty. For full details of warranty and service agreements, please contact the organisation which supplied the product to you.

Exclusions

The warranty does NOT cover:

1. Customer misuse, including incorrect installation.
2. Abnormal environmental operating conditions.
3. Damage incurred by accident, fire, lightning or other hazard.
4. Modification to the unit or inexpert / attempted repair.
5. Any other damage (other than manufacturing defects).
6. Improper packing or transit / courier damage.
7. Over voltage audio power supply used.
8. No fault found.

Application Solutions (Safety and Security) Limited shall not be liable for any indirect, special or consequential loss or damage (including without limitation any loss of profits) arising from the use of this product or for any breach of this warranty.

In the interest of continual product development, Application Solutions (Safety and Security) Limited reserves the right to make changes to product specification without notice or liability.

