



AK6070

## Spare Boom Microphone for Headset

Spare Boom Microphone for all A-Kabel type Headsets

Spare Part

# Specifications

|                 |                                  |
|-----------------|----------------------------------|
| Weight          | 0.1 kg                           |
| Microphone      | Pluggable, Dynamic, Boom type    |
| Impedance       | 240 Ohm+- 30 %                   |
| Sensitivity     | -57 dB+-3 dB, 0 dB=1v/pa at 1kHz |
| Frequency range | 50Hz-6KHz.                       |

## Used With



VMP-36-PEL-A

Headset with boom mic, headband, and 10m cable for VMP Station



VMP-36-PELP-A

Headset with boom mic, headband, and 10m cable



VMP-36-PEL-A/15

Headset with boom mic, headband, and 15m cable for VMP Station



VMP-36-PEL-A/20

Headset with boom mic, headband, and 20m cable for VMP Station



VSP-36-PEL-A

Headset with boom mic, headband, and 10m cable



VSP-36-PEL-A/20

Headset with boom mic, headband, and 20m cable



VSP-36-PELP-A

Headset with boom mic, headband, and 10m cable



VSP-36-PELP-A/20

Headset with boom mic, headband, and 20m cable



VSP-36-PELP-A/25

Headset with boom mic, headband, and 25m cable



P-MT7-A

Headset with boom mic, headband, and 10m cable



AK5850HS

Ex-approved Headset



P-9029

Headset with boom mic, headband, and 10m cable